



# TREK PZD700A

High voltage piezo driver/power amplifier for precise control of output voltages in customer specified bipolar or unipolar ranges within available range settings.



The Trek® PZD700A is a high-voltage DC-stable piezo driver/amplifier designed to achieve the accurate output responses and high slew rates demanded by reactive loads by utilizing a four-quadrant active output stage that sinks or sources current into reactive or resistive loads. The Trek PZD700A is configured as a non-inverting amplifier. An inverting configuration is available. Both configurations are available as either single or dual channel instruments. They are bench top operable or 19-in rack mountable.

## PRODUCT HIGHLIGHTS

- Four-quadrant output for driving capacitive loads
- Closed loop system for high accuracy
- Short-circuit protected for equipment protection
- All solid-state design for maintenance free operation
- DC-stable for programmable supply applications
- Low output noise for ultra-accurate outputs
- Model PZD700A M/S is also available with twice the current capability of the Trek PZD700A
- NIST-traceable Certificate of Calibration provided with each unit

## TYPICAL APPLICATIONS

- Piezoelectric driving/control
- Laser modulation
- MEMS
- Semiconductor research
- Piezoelectric vibration damping

## AT A GLANCE

### Output Voltage Range

**Bipolar:** 0 to  $\pm 700$  V DC or peak AC

**Unipolar:** 0 to  $+1.4$  kV DC or peak AC or 0 to  $-1.4$  kV DC or peak AC

### Output Current Range

**Bipolar:** 0 to  $\pm 100$  mA

**Unipolar:** 0 to  $\pm 50$  mA

### Slew Rate

**Bipolar:** Greater than  $380$  V/ $\mu$ s

**Unipolar:** Greater than  $370$  V/ $\mu$ s

### DC Voltage Gain

0 to  $300$  V/V, adjustable using a front panel potentiometer

# TREK PZD700A HIGH VOLTAGE POWER AMPLIFIER

## TECHNICAL DATA

Performance Specifications		
	Bipolar	Unipolar
Output Voltage Range	0 to $\pm 700$ VDC or peak AC	0 to +1.4 kV DC or 0 to -1.4 kV DC or peak AC
Output Current Range	0 to $\pm 100$ mA	0 to $\pm 50$ mA
Input Voltage Range	0 to $\pm 10$ VDC or peak AC	
Input Impedance	90 k $\Omega$ , nominal (non-inverting)	
	1 M $\Omega$ nominal, (inverting)	
DC Voltage Gain	0 to 300 V/V, adjustable using the front panel potentiometer	
DC Voltage Gain Accuracy	Better than 0.1% for factory set gain of 200 V/V (input to output)	
Offset Voltage	Less than $\pm 500$ mV	
Output Noise <sup>1</sup>	Less than 50 mV rms to 20 kHz for a 1 nF load	
	Less than 100 mV rms to 20 kHz with no load	
Slew Rate	Greater than 380 V/ $\mu$ s (10% to 90%, typical)	Greater than 370 v/ $\mu$ s (10% to 90%, typical)
Settling Time	Less than 50 $\mu$ s when critically damped	
Large Signal Bandwidth	DC to greater than 125 kHz (-3 dB)	DC to greater than 120 kHz (-3 dB)
Small Signal Bandwidth	DC to greater than 200 kHz (-3dB)	
Stability	Drift with Time: Less than 50 ppm/hr, noncumulative	
	Drift with Temp: Less than 100 ppm/ $^{\circ}$ C	

Voltage Monitor Specifications	
Ratio	1/200th of the high voltage output
DC Accuracy	Better than $\pm 0.1\%$ of full scale

Current Monitor Specifications	
Ratio	0.1 V/mA, $\pm 1\%$ of full scale
DC Accuracy	Better than $\pm 1\%$ of full scale

Mechanical Specifications	
Dimensions (H x W x D)	Single Channel: 110 x 220 x 445 mm (4.3 x 8.7 x 17.5 in)
Weight	Single Channel: 5 kg (11 lb)
HV Connector	SHV High Voltage Connector

Electrical Specifications	
Line Voltage	Factory Set for one of two ranges: 90 to 127 VAC or 180 to 250 VAC, either at 48 to 63 Hz
AC Line Receptacle	Standard three-prong with integral fuse holder
Power Consumption	Single Channel: 90 VA
	Dual Channel: 175 VA
HV Cable	2 m, 30.8 pf/ft @ 1 kHz, Nominal

Environmental Specifications	
Temperature	0 to 40 $^{\circ}$ C (32 to 104 $^{\circ}$ F)
Relative Humidity	To 85%, noncondensing
Altitude	To 2000 meters (6561.68 ft.)

<sup>1</sup> Measured using the true rms feature of the HP Model 34401A digital multimeter

## TECHNICAL DATA

Features	
Digital Enable	BNC connection for TTL compatible signal to turn ON/OFF the HV output for each channel
Gain Control	The gain of the Trek PZD700A is adjustable from 0 to 300 V/V
Dynamic Adjustment	A graduated one-turn front panel potentiometer is used to optimize the AC response of the output signal for various load configurations
Input Configuration	The input is configured as a non-inverting amplifier. An inverting amplifier is also available
Limit Indicator	An amber indicator warns when the Trek PZD700A fails to produce the required HV output
Automatic Power Limit	Automatically limits the internal power dissipation to protect the Trek PZD700A from overheating

## REFERENCE NUMBERS

The Trek PZD700A comes from the factory with settings for an output voltage of  $\pm 700$  VDC or peak AC, a voltage gain ratio of 200 V/V, with a non-inverting input. Please specify voltage range ( $\pm 700$  V, +1400V or -1400V) and input configuration (inverting or noninverting) when ordering. The Trek PZD700A M/S is also available with twice the current capability of the standard PZD700A.

PZD700A	
PN	Description
PZD700A-1-L	Single Unit, 90 to 127 VAC
PZD700A-2-L	Dual Unit, 90 to 127 VAC
PZD700A-1-H	Single Unit, 180 to 250 VAC
PZD700A-2-H	Dual Unit, 180 to 250 VAC

Included Accessories	
PN	Description
23439	Operator's Manual
43874R	HV Output Cable Assembly, cable and SHV mating connector
Varies	Line Cord, Spare Fuses, selected per geographic region



#### ABOUT ADVANCED ENERGY

Advanced Energy (AE) has devoted more than three decades to perfecting power for its global customers. AE designs and manufactures highly engineered, precision power conversion, measurement and control solutions for mission-critical applications and processes.

Our products enable customer innovation in complex applications for a wide range of industries including semiconductor equipment, industrial, manufacturing, telecommunications, data center computing, and medical. With deep applications know-how and responsive service and support across the globe, we build collaborative partnerships to meet rapid technological developments, propel growth for our customers, and innovate the future of power.

#### PRECISION | POWER | PERFORMANCE



For international contact information,  
visit [advancedenergy.com](http://advancedenergy.com).

[sales.support@aei.com](mailto:sales.support@aei.com)  
+1.970.221.0108

Specifications are subject to change without notice. Not responsible for errors or omissions. ©2020 Advanced Energy Industries, Inc. All rights reserved. Advanced Energy® Trek®, and AE® are U.S. trademarks of Advanced Energy Industries, Inc.